

SUPRA MAINS BLOCK MD-BE

Screened Mains block with NIF-filter

Rev.date: 2023-01-13

Customs tariff no: 8536901000

Country of origin: Sweden

Cable not included!



SUPRA Mains Block MD-BE (Belgium & France)

Supra LoRad MD mains blocks are designed to shield and filter noise. Supra NIF (Non-Intrusive Filtering), an efficient high frequency (RFI) transient filter. It is designed and configured to efficiently suppress RFI interference, but not to dampen quick recharge demands from the connected devices power supplies. Supra NIF is developed by Ben Duncan Research in England.sources. It is possible to order with custom configuration and have a capacity to suppress noise floor up to 40 dB!

Switch (optional), include also a high current in-rush capable on/off switch allowing for turning the entire equipment on or off.



All parts are made in Sweden or Germany & assambled in our factory in Ljungskile, Sweden.

- Noise damping up to 40 dB!
- Internal wiring of 2.5 mm² oxygen-free copper leads
- Support a staggering peak power 2400 Watt @ 230 Volt and 10 Ampere
- Protect both you and your gear from various alternating fields
- Wall mounted or standing on a flat hard surface. Rubber feet and brackets included
- Custom tailored NIF-filter from Ben Duncan Research in UK
- Shielded aluminum chassis prevents electric, electro-magnetic and magnetic fields



CONSTRUCTION

Chassis:	Aluminum
Standard:	Belgian/French Standard
Inlet socket:	SUPRA MCH-10, 10A
Outlet sockets:	2 to 6 x SUPRA MCH-16/BE, Schuko
Rated Current/Voltage:	10A / 250V / 2400W
Max RFI Noise damping:	40dB
Fuse:	Ceramic 10A, slow
Width & height (WxH):	90x50mm
Length (L):	MD02-BE = 164mm + 52mm for each additional socket
Standard filtering:	No filter on outlet no 1 for MD02-MD06 Increased filtering, the last socket got highest damping



All mains blocks can be ordered with or without filters for any of the sockets.
Power Amps are recommended to be connected to an unfiltered outlet.



PRODUCT	Qty	Part no.	EAN-13	Carton	Weight
MAINS BLOCK MD02-BE	1PC	3024000618	7330060207341	20	0,63
MAINS BLOCK MD04-BE	1PC	3024000584	7330060207297	20	0,89
MAINS BLOCK MD05-BE	1PC	3024000576	7330060207303	20	1,00
MAINS BLOCK MD06-BE	1PC	3024000188	7330060205705	20	1,21
MAINS BLOCK MD06-BE SWITCH	1PC	3024000857	7330060208287	20	1,25